

# PV Box RT

## Containerized plug and play power conversion system adapted to customer requirements and local standards

PV Box is a power conversion system. In a PV plant installation, it operates between DC field and AC MV grid connection point. The PV Box performs the DC power concentration, the DC/AC conversion and the AC voltage elevation to the grid voltage level. It ensures the protection of the maintenance people and the installation against electrical faults such as short-circuit and lightning. The optimized versions of the PV Box allow a reduction of the balance of systems cost, an increase of the reliability and an improvement of construction lead times.

### Why choose PV Box RT?



#### True bankability

- Warranty from a trusted partner with over 177 years of experience
- World leader in industrial power drives, UPS and electrical distribution
- Strong service infrastructure worldwide to support your global needs



#### Higher return on investment

- Compressed construction lead-times through factory integrated solution
- Reduced transportation, off-loading and on-site labor costs
- Enhanced uptime thanks to qualified and reliable designs



#### Designed for reliability

- Industrialized solution according to Schneider Electric proven industrial processes
- Equipment and integration made in Schneider Electric factories
- Configurable to withstand severe weather conditions: continental, tropical and deserts environments
- Undergone extensive safety, quality and reliability risk mitigation
- Proven robust design through rigorous Custom Reliability Testing
- Type-tested solution according to IEC-62271-202 including Arc Flash Testing (IAC-A)



#### Flexible

- Vast choice of power and AC medium voltage levels
- Suitable for most environmental conditions and local standards
- Configurable to be optimized for specific project needs



#### Easy to service

- Fully monitored solution
- Convenient and safe enclosure design for maintenance purposes
- Local Schneider Electric service and maintenance available in 100+ countries



#### Easy to install

- Ease in transportation due to its compact and light design (minimized width, height and length for easy shipping by road)
- Solution delivered pre-assembled, configured and tested to reduce on-site labor and project duration
- Integrated concrete basement requiring minimal civil works at site

### Product applications



PV power plants centralised



Commercial grid-tie centralised



Road transportation version

Device short name	PV Box RT 1080	PV Box RT 1260	PV Box RT 1360
<b>Electrical specifications</b>			
<b>DC input</b>			
Voltage range, MPPT	440 - 800 V (at PF=1)	510 - 800 V (at PF=1)	550 - 800 V (at PF=1)
Max. input voltage, open circuit	1000 V	1000 V	1000 V
Max. DC current	2 x 1280 A	2 x 1280 A	2 x 1280 A
<b>AC output</b>			
Nominal power	1080 kVA	1260 kVA	1360 kVA
Nominal voltage	up to 36 kV	up to 36 kV	up to 36 kV
Frequency	50 Hz	50 Hz	50 Hz
Power factor compensation	0.8 to 1.0 lead / lag	0.8 to 1.0 lead / lag	0.8 to 1.0 lead / lag
<b>Equipment</b>			
Inverters	2 x XC 540	2 x XC 630	2 x XC 680
DC connection	2 x DC Box 6 input or 2 x DC Box 10 input (+/-)		
DC fuse range <sup>(1)</sup>	DC Box 6: 315 A, 350 A, 400 A / DC Box 10: 160 A, 200 A, 250 A		
Transformer type	Schneider Electric Minera oil type ONAN		
Transformer losses	C0Bk		
Medium voltage switchgear U <sub>≤</sub> 24 kV	Schneider Electric RM6 ring main unit type NE-DI with Sepam 10 protection relay		
Medium voltage switchgear 24 kV ≤ U ≤ 36 kV	Schneider Electric Flusarc ring main unit type CB-C with Sepam 10 protection relay		
<b>Optional content</b>			
Automatic progressive reconnection <sup>(2)</sup>	MV circuit breaker motorization, configurable timer		
Auxiliary power transformer	10 kVA / 400 V		
DC input measurement	DC Box monitored		
Monitoring and control	Conext Control monitoring cabinet with secured power supply		
Safety kit	Fire-extinguisher, insulated MV rod and gloves, insulating stool		
Service kit	Contacts on doors and smoke detector (available with Conext Control option)		
Service contract	Worldwide service team - consult your sales representative for service offer		
<b>External operating conditions</b>			
<b>Temperature</b>			
Standard temperature range	-20°C / + 45°C <sup>(3)</sup>		
Other temperature ranges	Temperate, continental, desert, tropical (consult your sales representative)		
<b>Pollution</b>			
Standard low polluted environment (Rural and suburban environment)	G4 filters		
Option polluted environment (desert, urban...) <sup>(4)</sup>	External filter box (G4 and F9 filters, fans, speed drives)		
<b>Other conditions</b>			
Max. relative humidity (non condensing)	100%		
Max. altitude above sea level <sup>(5)</sup>	2000 m		
Max. wind speed	123 km / h		
Max. snow load	250 kg / m <sup>2</sup>		
IP grade LV and MV compartment	IP54		
IP grade transformer compartment	IP23		
<b>General specifications</b>			
<b>Dimensions and weight</b>			
During transportation (H x W x D)	3.10 x 2.50 x 8.90 (or 9.70 <sup>(6)</sup> ) m		
Assembled on site (H x W x D)	2.65 x 3.15 x 8.90 (or 9.70 <sup>(6)</sup> ) m		
Weight approx. with standard content	24 tons		
<b>Material</b>			
Basement	Concrete basement included		
Walls and roof	Sandwich panels		
<b>Cooling</b>			
LV and MV switchboard compartment	Ensured by inverter fans. <sup>(7)</sup>		
Transformer compartment	Natural		
<b>Regulatory approval</b>			
Electrical standards	IEC 62271-202, IEC 61439, IEC 62271-200, IEC 60076		
Type-test certification	IEC 62271-202		
Internal arc classification (acc. to IEC 62271-202)	IAC-A		
General ventilation filters standard	EN779:2012		
Building standards	Eurocodes		

Specifications are subject to change without notice.

<sup>(1)</sup>Fuses may be ordered separately. <sup>(2)</sup>To avoid simultaneous reconnection of every PV Boxes and for automatic opening and reclosing on grid voltage loss (grid requirement). <sup>(3)</sup>Derating above 40°C.

<sup>(4)</sup>For dust or sand (IEC 60721-2-5 (§4.2.4)) size<150 µm and concentration<2 mg / m<sup>3</sup>. <sup>(5)</sup>Power derating above 1000 m. Above 2000 m special requirements. <sup>(6)</sup>In case of filter box option.

<sup>(7)</sup>Extra fans in filter box only for polluted environment.